



# (XF-ØEFP)

## PEAK ROOF FLASHING Installation Instructions

---

The Peak Roof Flashing is adjustable to any roof pitch between 1/12 and 12/12.

1. Mark the chimney centerline on the roof. Since you don't want to cut a roof truss make sure you are at least 7" away from a truss. If you are closer than 7" you will need to offset the chimney accordingly.
2. Cut an opening in the roof center on the mark previously made. See Figure 1 for the opening dimensions. You need to respect those dimensions for the flashing to fit properly and to make sure you will have at least 2" clearance between the chimney outer casing and combustible material.
3. Unfold and bend the adjustable tabs on either side of the peak flashing to meet the pitch of the roof and insert the flashing into the hole that has been cut out. Secure the flashing in place by nailing or screwing the tabs to the roof using roofing nails or roofing screws (Figure 2). Don't forget to seal the joint between the adjustable tabs and the roof with roofing tar or silicone.
4. Determine the angle of the two adjustable side cover plates by bending them over the ridge to meet the pitch of the roof. Attach the side plates to the flashing with self-tapping screws. Be sure to apply some silicone between the side plates and the flashing before screwing them in place.
5. Install the flashing by nailing or screwing it to the roof. Make sure to apply roofing tar between the flashing and the roof.
6. Ensure that any potential leakage points are well sealed with silicone, some potential places are shown in Figure 3.
7. Install chimney sections until the required chimney height is reached.
8. Install the storm collar and rain cap according to the ICC Excel installation manual. The Caulking roll (ECR) or silicone can be used to seal the storm collar to the chimney.

Roof Slope / Inclinaison du toit	A		
	6"Ø	7"Ø	8"Ø
4/12	6 1/2	7	7 1/2
5/12	6 3/4	7 1/4	7 3/4
7/12	7 1/4	7 3/4	8 1/4
8/12	7 1/2	8	8 3/4
12/12	8 3/4	9 1/2	10 1/4
	B		
	6"Ø	7"Ø	8"Ø
	12 3/8	13 3/8	14 3/8




FIGURE #1




FIGURE #2




FIGURE #3

SCELLER AVEC DU SILICONE

### Liste de contrôle / Check List:

- 1 Solin de pignon / Peak Roof Flashing
- 1 sac avec 8 vis / 1 bag containing 8 screws
- Notice d'installation et liste de contrôle / Instructions and check list